

The Steps for Updating the 2488

**Updating the 2488 is a unidirectional upgrade.
You will not be able to downgrade to the previous version.
Before proceeding, backup your data to CD or to your computer.**

Step 1: Burn your Disc Image.

For Roxio Easy CD Creator

- 1) **Open** Roxio Easy CD Creator.
- 2) Select **CREATE DATA CD** from the menu.
- 3) Under **FILE**, select **CREATE CD FROM IMAGE...**
- 4) In the **Files of Type** window, choose **"ISO IMAGE FILES (*.iso)"**
- 5) Browse to the location of the downloaded image file.
- 6) Select the file **"2488vxxx.iso "**(version of the file you are updating to) and click **OPEN**.

For Nero

- 1) Go to **Recorder** from the top menu and select **"BURN IMAGE"**.
- 2) Browse to the location of the downloaded image file.
- 3) Select the file **"2488vxxx.iso"** and hit **OPEN**.
- 4) At the Burn Compilation Window, select **BURN**.

For Mac OSX Panther

- 1) Go to your **Disk Utility** located in **Hard Disk/Applications/Utilities**.
- 2) From the **Image** menu at the top of the screen, select **BURN**.
- 3) Browse to the location of the downloaded image file.
- 4) Select the file **"2488vxxx.iso "** and hit **OPEN**.

For Mac OSX Jaguar

- 1) Go to your **Disk Copy** located in **Hard Disk/Applications/Utilities**.
- 2) Under the **File** Menu at the top of the page select **"BURN IMAGE"**.

For Toast Titanium 6

- 1) Open **Toast** and select **COPY** from the Main Menu.
- 2) Click on **IMAGE FILE**.
- 3) **Drag** the downloaded **2488vxxx.iso** file into Toast.
- 4) Click on the **RED BUTTON** at the bottom right of the window.

Step 2: Update the 2488.

- 1) **Shutdown the 2488**
- 2) **Unplug** everything from the 2488 except the **POWER CORD**.

- 3) While holding down the **MONITOR SOURCE** and the **SHUTDOWN** buttons turn on the power.
- 4) When you see “**PREPARE UPDATE**” on the screen let go of the Buttons.
- 5) The CD tray will open, **insert the CD** and press **YES/ENTER**.
- 6) The display will then show the new version.
- 7) Press **YES/ENTER** to update the 2488.

- 8) *******VERY IMPORTANT! ******* THE POWER TO THE 2488 MUST NOT BE INTERRUPTED AT THIS TIME. POWER LOSS DURING THE UPDATE WILL RESULT IN DAMAGE TO THE 2488.
- 9) When the update is completed you will be prompted to shutdown the power. **Remove the CD from the tray** and **power off** the 2488.

Step 3: Confirm the Update

- 1) Press the **POWER BUTTON** on the back of the 2488.
- 2) On the Boot up screen you should see “**Ver. x.xx Build xxxx**”(version you have updated to)
- 3) You have successfully updated your 2488